Eartips (8 pairs)

Charging Case

Innovating the Art of Listening





Owner's Guide




| ophone | |
|-------------|--|
| cator Light | |
| | |

when you place them back in the charging case.











| 3 | Indicator Light | Use Left Earbud Only |
|---|---------------------|--|
| 2 | Microphone | The rea and blue EED 5 Will stop hashing. |
| 1 | Music & Call Button | The red and blue LED's will stop flashing. |
| | | HIFIMAN TWS600. Once paired, you will |

The earbuds will power on automatically when removed

Use Right Earbud Only Remove the right earbud from the case, press the button until

you hear power off. Continue to press you will first hear **Attention:** When you first use the product, please allow the case and earbuds inside to fully charge, up to 1.5 hou





HIFIMAN TWS600. Once paired, you will hear "Connected".

Please keep the right earbud in the charging case. The left one

will enter one-sided mode automatically to return to stereo simply remove the right earbud from the charging case.

The earbuds will turn off and begin recharging automatical

power on, until you heard pairing. Then you can connect with the right earbud only. When you wish to return to stereo

The left earbud connects to your device only.

The left and right earbuds can be used as single channel headphones

The right earbud will connect the left one.



left earbud out first. After it connects to your device then simply return to stereo by bringing the right earbud out

Place the earbuds in the charging case and close the lid.

double-press the right earbud to increase volume.



Calls battery case and earbuds. One-to-four LED lights will

right earbud.

mode, put both earbuds in the charging case, then bring the



best one for your ear to get the best experience. You may need different size eartips for left ear and right ear.

More than one eartips' size may fit you. Please choose the



X Triple-press the left earbud to turn to the next track. **Charge the Charging Case** triple-press the right earbud to turn to previous trace

Insert earbuds with the eartips to your ear directly. Twist gently until they fit your ear perfectly and feel comfortable.

Calls are initiated and answered with either the left o

The red light will turn on when charging,

and a blue light will appear when finished.

the earbuds in the charging case.

buds indicate charging is complete.

Note: Some eartips may not fit properly in the case.

Oversized tips may need to be removed before placing

appear, indicating the case and earbuds. Up to four will be

words "Battery Low" will be heard every 20 seconds.

visible: One light indicates minimal power remains, and four

Charge the Earbuds



Insert a Type-C USB cable into the socket to charge the





* Press once to accept an incoming call, or press and hole 2 seconds to reject. When the battery power is low or entirely drained, the X Press once to end the call.

> When you are talking on the phone and receive anothe incoming call: Press once to end the first call and answer new coming call.

Charging Light keeps steady red
Pairing Blinking blue and red Press and hold two seconds to activate the phone's voice control

Charging One-to-four lights are visible while charging

Please do not remove or replace the internal battery,

The Right and Left Earbud Pairing Guide (only use

A pink-blue flashing appears twice and then turn off

4. Please try to pair with your Bluetooth equipment again.

doing so will void your warranty automatically.

User Guide

Charging Case Status Light

Basic Specification of Earbud

Length: 25mm Width: 17.4mm Height: 26mm

Avoid high listening volume to prevent hearing loss.

- arbud charging time 1H

Single head weight

F transmission power | Cla Press the both earbuds for 6 seconds to power off ransmission range (Hz) 2.40GHz~2.48GHz Transmission distance | >10m,up to 50m (depending on the environmen. 2. Press the both earbuds for about 12 seconds.

3. Press the both earbuds for 2 seconds to restart.

Operation is subject to the following two conditions: (1) This device may not cause harmful interference, ar

2. Changes or modifications not expressly approved by Do not use the TWS600 when driving a car, cycling, near

without RF striction.

FCC STATEMENT

traffic or in any dangerous environment requires full

after charging. Permanently on charge may shorten

When the earbud can not be automatically paired) etooth version Bluetooth HIFIMAN recommends using the original Type-C USB

Audio coding format | CVSD, mSBC, SBC, ACC

Safety Information

The two earbuds will paired with each other automatically when they're close to each other. Specification of Charging Case

HIFIMAN warrants this product to be free of defects in materia (2) This device must accept any interference received including interference that may cause undesired operati

The device has been evaluated to meet general RF expo

NOTE: This equipment has been tested and found to com

FCC Rules. These limits are designed to provide reasonable

protection against harmful interference in a residential

with the limits for a Class B digital, pursuant to Part 15 or the

--- Connect the equipment into an outlet on a circuit different

--- Consult the dealer or an experienced radio/ TV technician

from that to which the receiver is connected.

party responsible for compliance could void the user's authority to operate the equipment.

To maximize battery life, disconnect the USB cable

The device can be used in portable exposure condition

charging cable. The maximum input should be 5V/1.5A. An unsupported third-party cable may damage the case or earbuds. If you are using an unsupported charger if may cause damage.

accordance with the instructions, may casue harmful Please note that If using TWS600 to watch videos or for interference to radio communications, However, there is no gaming, the audio will be slightly delayed. This is guarantee that interference will not occur in a particular

unavoidabledue to the latency of Bluetooth transmis

1. This device complies with Part 15 of the ECC Rules.

or workmanship for a period of one year from the date of original retail purchase. If your product is found to be defective during the warranty period, HIFIMAN will, at its sole option

HIFIMAN Limited Warranty

factory reconditioned or substantially equivalent model. The limited warranty does not apply to any defects attributable t FCC Radiation Exposure Statement: damage beyond the reasonable control of HIFIMAN including

> damage caused by abuse, misuse, misapplication or modifications performed by anyone other than HIFIMAN

If your product is under warranty and problem appears, please with your product, simply contact your authorized dealer or contact HIFIMAN customer service or your authorized dea HIFIMAN directly (if purchased from us) and explain the issue in If necessary, and at our discretion, we will provide a warrant detail, Should a return be required, a RMA# will be issued, Return repair or replacement of your product. shipping to HIFIMAN or authorized service facility will be at the


installation. This equipment generates, uses and can radiate Caution: do not disassemble or modify the product in any way. radio frequency energy and, if not installed and used in Tampering with or modifying your HIFIMAN product will void its

either repair the product or replace the product with a new o

installation. If the equipment does cause harmful interfere This Limited Warranty does not apply to:


- to radio or television reception, which can be determined by Defective or discolored parts if the damages are caused by turning the equipment off and on, the user is encouraged t fluids, dirt, missing keys, broken plastic parts or improper us
- try to correct the interference by one or more of the 2. Damage caused by misuse with another product. following measures: 3. Use of the product for other than its normal intended use,
- --- Reorient or relocate the receiving antenna. including, with out limitation, failure to use the product in --- Increase the separation between the equipment ar accordance with the supplied "Owner's Guide"


HIFIMAN Limited Warranty



6. Damage caused by services/repairs or other modifications to

- the system carried out by anyone other than HIFIMAN or an authorized HIFIMAN distributor or dealer.
- 7. Damage caused by self-repair or if the unit has been disassembled or modified in any way.





owner's expense.

authorized HIFIMAN dealer, or email us directly at customerservice@HIFIMAN.com

For any further information or questions, please contact your



twitter.com/hifimanofficial



www.hifiman.com

Innovating the Art of Listening

FACEBOOK

Scan QR Code to join

HIFIMAN on facebook